


VOLTSTAR™

VOLTGUARD


— AVS7A




High Voltage



Low Voltage



Spikes/Surges



Power-Back Surges



Basic Lightning

Nominal Voltage	230V
Current Rating	7Amps
Frequency	50/60Hz
Under/over-Voltage Disconnect	185V/260V
Under/over-Voltage Reconnect	190V/258V
Spike Protection	160J
Wait Time	30seconds

→ Protects against high and low voltage, brown-outs and voltage dips. These conditions are harmful to electrical and electronic equipments. Typical Applications: All sensitive electrical and electronic equipments, especially for TV, Video, Hi-Fi, Fax, Photocopier, Cash Registers, Electronic Scales, Notebook, PC setc.

By disconnecting the power when it is bad, the VoltGuard safeguards against short term and long term damage to ensure higher efficiency from your appliances. 30 seconds start-up delay is built-in to ensure stability of the power supply.

VOLTGUARD CONNECTION DIAGRAM



Any electrical or electronic appliance

